

Flokk Service Mode menu overview

Your Flokk provides configuration and problem resolution features that are not required for day to day operations.

These features are available when your Flokk is in “Service mode”

To access Service Mode:

If your Flokk is Turned **on**, from the “Ready” screen:

1. Press the “Done” button
2. From the menu offered, select the “Service mode” option

If your Flokk is turned **off**:

1. Press and hold any button
2. Turn on your Flokk
3. When the message “Starting Service” is displayed, release the button.

Press the “ACTION” button on the “Service Ready” screen.

Action menu

| | |
|-------------|--|
| NONE | Take no action and return to “Service Ready” screen. |
| File | Enter file mode so you can connect your Flokk to a computer with a USB cable and access the files on it. |
| Backup | Send a copy of all the files on your Flokk to your private account at flokk.ca. |
| Recover | Overwrite the files on your Flokk with one of the set of back up files stored by you at flokk.ca. |
| Wizard | Start a configuration Wizard session |
| Link | Link your Flokk to your account at flokk.ca. |
| Submit logs | Copy the log files of your Flokk’s recent operations to flokk.ca so they can be used by Flokk personnel to investigate an issue. |
| | DO NOT select this item unless directed by Flokk service personnel. |

Action menu options continue at top of next column

Action menu (continued)

| | |
|----------------|--|
| Remote service | Enable remote access to your Flokk by Flokk service personnel so they can provide you with assistance. |
| | DO NOT select this item unless directed by Flokk service personnel. |
| Remote off | Disable remote access to your Flokk |
| Self test | Test all the components of your Flokk. |
| SHUT DOWN | Turn off or restart your Flokk. |
| | Go to Shut down menu |

Press “SETUP” button on the “Service Ready” screen

Setup menu

| | |
|---------------|--|
| NONE | Return to the “Service Ready” screen. |
| Connect WiFi | Select a WiFi network currently available to the Flokk, and provide the WiFi network password if one is required and has not been provided before. |
| Update | Update the software on your Flokk. |
| Set time zone | Select the time zone that you want your Flokk to operate in. |
| Factory reset | Clear all files from the Flokk and return all configuration settings to their original values. |

Ether:

- From the “Service Ready” screen, Press the “Done” button.

or:

- Select the “SHUT DOWN” option from the “Action” menu.

Shut down menu

| | |
|-------------|--|
| CONTINUE | Return to the “Service Ready” screen. |
| POWER OFF | Prepare your Flokk to have the power switch turned off. DO NOT move the power switch to the off position until the message “Safe to switch power off.” is displayed. |
| Start Flokk | Exit Service Mode and start Flokk herd management operations. |
| Restart | Restart your Flokk. |

Notes:

- Every item in a menu will not always be offered. Your Flokk will present those options that can be completed at the time the menu is displayed.
- In particular, features that require access to flokk.ca will not be offered if your Flokk can not access a WiFi network.
- Some of these options require a pad subscription, and will not be offered if you are not currently subscribed to the related service. See flokk.ca for complete information.
- Read “GETTING STARTED.pdf”, located on your Flokk, to learn how to set up and use your Flokk.
- Refer to the “Flokk user reference manual.pdf”, located on your Flokk. for complete and detailed information.